

6150RF

Deluxe Fixed English Integrated Keypad/Receiver



Add wireless technology to any new installation with Honeywell's 6150RF Keypad—a unique, breakthrough product that offers the unbeatable combination of attractive convenience features and competitive value in a single, quick-install package. The integrated design solves even the trickiest installation challenges and reduces costs by letting you add full wireless capability to any compatible VISTA control—without additional wiring or sacrificing zones.

FEATURES:

- 6150 Deluxe Keypad
- 5881ENM 16-Zone Wireless Receiver
- 5800TM Status Transmitter
- On-board relay
- Single four-wire run is all that's required
- It is the ideal choice where wireless keys are to be used:
 - Keys can be programmed at the panel, just as they would with the 5881ENM
 - Keys can be enrolled locally at the keypad, without taking up additional zones at the control
- Fully compatible with all 5800 wireless devices

- The 5800TM module needed to support the 5804BD and 5804BDV is already built in
- Supports encrypted operation of the 5804E and 5804BDV four-button keys
- On-board single relay provides a low cost solution for opening garage doors. With a four-button remote key, a key can be assigned for the garage door

Stylishly Designed

- Sleek white design blends with any décor
- Contoured, removable door lets customers customize the keypad for the look they want
- With the door closed the keypad has a smooth, unobtrusive appearance

Easy to Operate

- The fixed English display is easy to read, with large characters and simplified descriptions
- The sounder beeps to help identify security system status
- Comfortable soft-touch keys labeled with simple commands are illuminated for nighttime visibility
- Four larger function keys can be programmed for one touch operation and are accessible even when the door is closed

SPECIFICATIONS:

Dimensions

- 4-7/8" H x 6" W x 1"D
(125mm x 160mm x 25 mm)

Sounder

- Piezo Electric

Wiring

- - (Black): Ground
- + (Red): +12 VDC (Aux. Power)
- D1 (Green): "Data In" to control panel
- D0 (Yellow): "Data out" from control panel

Current

- Standby: 80ma
- Activated: 105ma

ORDERING:

6150RF Keypad/Receiver

Honeywell Security & Custom Electronics
Honeywell International Inc.
PO Box 9035
Syosset, NY 11791
www.honeywell.com

L/6150RF/D
February 2005
©2005 Honeywell International Inc.

Honeywell